Message Flow Details

MM00231 - Disputed Readings or Missing Readings on Change of Supplier

Market Message Information

Market Message Reference	MM00231
MM Description	Notification of a disputed/missing Meter Readings on Change of Supplier and the associated details.
Local Catalogue Reference	D0300
Version	001
Notes	Although each address line in this flow is optional, the address itself is mandatory and must be included in the flow in Standard Address Format (SAF).

Scenario Variants

Scenario Variant	Name	Source	Target	Owner	Api Route	Api Method
SV00231	Disputed Readings or Missing Readings on Change of Supplier	Non Half Hourly Data Collector	Electricity Supplier	Retail Energy Code Company		

SV00232	Disputed Readings or Missing Readings on Change of Supplier	Electricity Supplier	Non Half Hourly Data Collector	Retail Energy Code Company	
SV00233	Disputed Readings or Missing Readings on Change of Supplier	Electricity Supplier	Electricity Supplier	Retail Energy Code Company	

Data Items

Data Item Number	Local Catalogue Reference	Name
DI50003	J0003	MPAN Core
DI50004	J0004	Meter Id (Serial Number)
DI50007	J0010	Meter Register Id
DI50008	J0012	Additional Information
<u>DI50019</u>	J0040	Register Reading
DI50097	J0171	Reading Type
DI50137	J0263	Metering Point Postcode
<u>DI50455</u>	J0924	Effective from Settlement Date {REGI} for New Supplier
<u>DI50488</u>	J1036	Metering Point Address Line 1
<u>DI50489</u>	J1037	Metering Point Address Line 2
<u>DI50490</u>	J1038	Metering Point Address Line 3
DI50491	J1039	Metering Point Address Line 4

DI50492	J1040	Metering Point Address Line 5
DI50493	J1041	Metering Point Address Line 6
DI50494	J1042	Metering Point Address Line 7
DI50495	J1043	Metering Point Address Line 8
DI50496	J1044	Metering Point Address Line 9
DI50632	J1265	Change of Supplier Reading Rejection Code
DI50985	J1659	Proposed Register Reading
DI50986	J1660	Status of Proposed Reading(s)
DI50989	J1663	Record Rejection Reason Indicator
DI51029	J1703	MPAN Core Process
<u>DI51030</u>	J1704	Initiating Flow Indicator

Flow Structure

SV00231 - Disputed Readings or Missing Readings on Change of Supplier - Message Structure

Group ID	Group Description	Range	Condition	L1	L2	2L3	L2	1L5	L6	L7	L8	Data Item Name	Data Item Rule
58C	MPAN Details	1-*	- Please reference Address Population Guidance v1.0.	G									
					1							MPAN Core	
					1							MPAN Core Process	
					1							Effective from Settlement Date {REGI} for New Supplier	

			0					Metering Point Address Line 1
			0					Metering Point Address Line 2
			0					Metering Point Address Line 3
			0					Metering Point Address Line 4
			0					Metering Point Address Line 5
			0					<u>Metering Point Address</u> Line 6
			0					Metering Point Address Line 7
			0					Metering Point Address Line 8
			0					Metering Point Address Line 9
			 0					Metering Point Postcode
			0			 	_	Additional Information
			0					Record Rejection Reason Indicator
59C	Meter Id	1-*	G					
				С				Meter Id (Serial Number)
			ŕ	1				Initiating Flow Indicator
60C	Meter Register Details	1-*	(G				
				1	0			Meter Register Id For MHHS Metering

							Points, this Data Item should be populated with details of the <u>Gc</u> umulative Rregister Rcading for
							Smart Metering Assets.
				С		Register Reading	
			(С		Reading Type	Reading Type value relates to the Proposed Register Reading data item.
				С		Change of Supplier Reading Rejection Code	
				С		Proposed Register Reading	
				1		<u>Status of Proposed</u> <u>Reading(s)</u>	

Commented [SJ1]: 10241 update - amending the Data Item Rule to remove reference to the cumulative register 'reading' as the data item is identifying the register itself.