

Message Flow Details

MM00021 - Request to Change Energisation Status

Market Message Information

Market Message Reference	MM00021
MM Description	A request for the energisation status of a metering point to be changed.
Local Catalogue Reference	D0134
Version	001
Notes	Half hour Data Collectors are not involved in the change of energisation process. This flow is not for use with prepayment meters. Though all of the address data items included in this flow are defined within the structure as being optional, the address itself is mandatory and must be included in the flow. The use of any individual address item cannot be made mandatory as, in the absence of an agreed address structure for all flows, an address may be constructed from any combination of the Address Line and Postcode items. - Where an AMVLP (Asset Metering Virtual Lead Party) is involved, the MPAN Core must contain an AMSID (Asset Metering System Identifier) and not an MPAN

Scenario Variants

Scenario Variant	Name	Source	Target	Owner	Api Route	Api Method
SV00021	Request to Change Energisation Status	Electricity Supplier	Distribution Network Operator	Retail Energy Code Company		
SV00022	Request to Change Energisation Status	Electricity Supplier	Electricity Meter Equipment Manager	Retail Energy Code Company		
SV00460	Request to Change Energisation Status	Asset Metering Virtual Lead Party	Electricity Meter Equipment Manager	Retail Energy Code Company		
<u>SVxxxxx</u>	<u>Request to Change Energisation Status</u>	<u>Electricity Supplier</u>	<u>Electricity Smart Meter Equipment Manager</u>	<u>Retail Energy Code Company</u>		
<u>SVxxxxx</u>	<u>Request to Change Energisation Status</u>	<u>Electricity Supplier</u>	<u>Electricity Advanced Meter Equipment Manager</u>	<u>Retail Energy Code Company</u>		
<u>SVxxxxx</u>	<u>Request to Change Energisation Status</u>	<u>Asset Metering Virtual Lead Party</u>	<u>Electricity Advanced Meter Equipment Manager</u>	<u>Retail Energy Code Company</u>		

Flow Structure

MM00021 - Request to Change Energisation Status - Message Structure

Group ID	Group Description	Range	Condition	L1	L2	L3	L4	L5	L6	L7	L8	Data Item Name	Data Item Rule
255	MPAN Cores	1-*	- Please reference Address Population Guidance v1.0.	G									
				1								MPAN Core	
				0								Metering Point Address Line 1	
				0								Metering Point Address Line 2	
				0								Metering Point Address Line 3	
				0								Metering Point Address Line 4	
				0								Metering Point Address Line 5	
				0								Metering Point Address Line 6	
				0								Metering Point Address Line 7	
				0								Metering Point Address Line 8	
				0								Metering Point Address Line 9	
				0								Metering Point Postcode	
				1								Energisation Status	
				1								Requested Energisation Status	
				0								Appointment Date	

				O							Earliest Appointment Time	
				O							Latest Appointment Time	
256	Meter Detail per MPAN Core	0-*	- Please reference Address Population Guidance v1.0.	G								
					1						Meter Id (Serial Number)	
					1						Meter Location	
					O						Customer Name	
					O						Mailing Address Line 1	
					O						Mailing Address Line 2	
					O						Mailing Address Line 3	
					O						Mailing Address Line 4	
					O						Mailing Address Line 5	
					O						Mailing Address Line 6	
					O						Mailing Address Line 7	
					O						Mailing Address Line 8	
					O						Mailing Address Line 9	
					O						Maximum Power Requirement	
					O						Contact Name	