

Message Flow Details

MM00121 - Notification of Failure to Install or Energise Metering System

Market Message Information

Market Message Reference	MM00121
MM Description	Notification that a meter could not be installed or a system energised due to faults or access problems.
Local Catalogue Reference	D0221
Version	001
Notes	Though all of the address data items included in this flow are defined within the structure as being optional, the address itself is mandatory and must be included in the flow. The use of any individual address item cannot be made mandatory as, in the absence of an agreed address structure for all flows, an address may be constructed from any combination of the Address Line and Postcode items. - . - Where an AMVLP (Asset Metering Virtual Lead Party) is involved, the MPAN Core must contain an AMSID (Asset Metering System Identifier) and not an MPAN.

Scenario Variants

Scenario Variant	Name	Source	Target	Owner	Api Route	Api Method
SV00121	Notification of Failure to Install or Energise Metering System	Electricity Meter Equipment Manager	Electricity Supplier	Retail Energy Code Company		
SV00471	Notification of Failure to Install or Energise	Electricity Meter Equipment Manager	Asset Metering Virtual	Retail Energy Code Company		

	Metering System		Lead Party			
SVxxxxx	Notification of Failure to Install or Energise Metering System	Electricity Smart Meter Equipment Manager	Electricity Supplier	Retail Energy Code Company		
SVxxxxx	Notification of Failure to Install or Energise Metering System	Electricity Advanced Meter Equipment Manager	Electricity Supplier	Retail Energy Code Company		
SVxxxxx	Notification of Failure to Install or Energise Metering System	Electricity Advanced Meter Equipment Manager	Asset Metering Virtual Lead Party	Retail Energy Code Company		

Flow Structure

MM00121 - Notification of Failure to Install or Energise Metering System - Message Structure

Group ID	Group Description	Range	Condition	L1	L2	L3	L4	L5	L6	L7	L8	Data Item Name	Data Item Rule
504	MPAN Cores	1-*	- Please reference Address Population Guidance v1.0.	G									
					1							MPAN Core	
						0						Metering Point Address Line 1	
						0						Metering Point Address Line 2	
						0						Metering Point Address Line 3	

					0															Metering Point Address Line 4		
					0																Metering Point Address Line 5	
					0																Metering Point Address Line 6	
					0																Metering Point Address Line 7	
					0																Metering Point Address Line 8	
					0																Metering Point Address Line 9	
					1																Appointment Date	
					1																Site Visit Check Code	
					0																Additional Information	